

#	Desired value	Description	Data type	Default value
0	0: OFF , 1:ON , 2:Last state	Relay state when powering on	Unsigned int	2
1	Off = 0, Red = 1, Green = 2, Yellow = 3 Blue = 4, Purple = 5 Cyan = 6, White = 7	Release color LED status	Unsigned int	4
2	Off = 0, Red = 1, Green = 2, Yellow = 3 Blue = 4, Purple = 5 Cyan = 6, White = 7	Touch color LED status	Unsigned int	3
3	0-49	Standby brightness	Unsigned int	33
4	51-100	Working brightness	Unsigned int	100
5	0 ~ 10	Buzzer sound level	Unsigned int	5
6	0: OFF , 1:ON	Cleaning mode	Unsigned int	0
7	0=disable , 1=CH1&Ch2 , 2=CH3&Ch4, 3=CH1&Ch2 and CH3&Ch4	Blind mode	Unsigned int	0
8	1~120 Second	Blind timer	Unsigned int	30
9	0=Cancel report status to home center, 1=Normal working	Report status	Unsigned int	0
10	0-7 (low to high)	Button 1 Sensitivity	Unsigned int	4
11	0-7 (low to high)	Button 2 Sensitivity	Unsigned int	4
12	0-7 (low to high)	Button 3 Sensitivity	Unsigned int	4
13	0-7 (low to high)	Button 4 Sensitivity	Unsigned int	4
14	Red = 1, Green = 2, Yellow = 3 Blue = 4, Purple = 5 Cyan = 6, White = 7	0-10V dimmer LED status color	Unsigned int	1